

12. ECCKT - Exchange Company Circuit ID

This field is NOT APPLICABLE for BellSouth.

13. PORTED # - Ported Telephone Number

Identifies the telephone number to be retained.

USAGE: This field is required.

DATA CHARACTERISTICS: 12 numeric characters. (including 2 preprinted hyphens)

EXAMPLE:

9	0	8	-	6	9	9	-	7	0	0	0
---	---	---	---	---	---	---	---	---	---	---	---

14. TNP - Total Number of Paths

Identifies the total number of talk paths, including the initial path, associated with the ported number.

USAGE: This field is conditional.

Required when the ACT field on the LSR Form is "C" or "V" and the NPT field is "B," otherwise prohibited.

DATA CHARACTERISTICS: 3 numeric characters.

VALID ENTRIES: 001 - 999

EXAMPLE:

0	0	1
---	---	---

15. CFTN - Call Forward To Number

Identifies the telephone number to which calls will be directed.

USAGE: This field is conditional.

Required when the ACT field on the LSR Form is "C" or "V" and the NPT field is "B," otherwise prohibited.

DATA CHARACTERISTICS: 12 numeric characters. (including 2 preprinted hyphens)

EXAMPLE:

6	0	9	-	5	5	5	-	1	5	5	5
---	---	---	---	---	---	---	---	---	---	---	---

16. NPT - Number Portability Type

Indicates the type of number portability for this request.

USAGE: This field is conditional.

Required when the ACT field on the LSR Form is "C" or "V"; otherwise optional.

DATA CHARACTERISTICS: 1 alpha character

VALID ENTRIES: A = DID
B = RCF
C = Route Index
D = Local Routing Number (Local Number Portability)

EXAMPLE:

A

17. RTI - Route Index

Identifies the routing index to be used by the provider's switching equipment to forward port the provider's telephone number to the customer's non-RCF trunk group.

USAGE: This field is optional.

DATA CHARACTERISTICS: 6 alphanumeric characters.

EXAMPLE:

2	1	5			
---	---	---	--	--	--

18. NPTG - Number Portability Trunk Group

Identifies the two six code (TSC) of a dedicated trunk group, from the porting switch to the customer's point of interface (POI), used to complete NP calls.

USAGE: This field is optional.

DATA CHARACTERISTICS: 8 alphanumeric characters.

EXAMPLE:

A	K	1	2	3	4	5	6
---	---	---	---	---	---	---	---

19. BA - Blocking Activity

Indicates the activity for the blocking of calls.

USAGE: This field is conditional.

Required when the BLOCK field is populated, otherwise optional.

DATA CHARACTERISTICS: 1 alpha character

VALID ENTRIES: A = Add
D = Delete
N = No change
Z = Remove all blocking

EXAMPLE:

D

20. BLOCK - Block

Identifies the type of blocking on the telephone number.

USAGE: This field is conditional.

Prohibited if the NPT field is "B," otherwise optional.

ONLY SELECT 1 VALID ENTRY.

DATA CHARACTERISTICS: 9 alphanumeric characters.

VALID ENTRIES: A = No Collect and third party
B = No third party
C = No collect call
1 = 1-, 0-, 0-, 00-, 01-, 011-, 411, PULSELINK, 976, 900, N11
2 = 0-, 0-, 00-, 01-, 976, PULSELINK
3 = 1-, 0-, 0-, 00-, 01-, 011-, 900
4 = 900, 976
5 = 976
6 = 900, 976, N11
7 = 011, 10XXX+011
8 = CREX1 WITH OPTIONAL CALLING PLAN
9 = CREX2 WITH OPTIONAL CALLING PLAN
W = 0-, 0-, 00-, 01-, 976, 011-
X = 976, 900, 011-
Y = 976, 900, N11, 011-
Z = 976, 011-
T = 1-, 10XXX1-, 976, 900 (SENDS ANI7) (casual calling)
U = 1-, 10XXX1-, 976, 900 (SENDS ANI7) OCP (NC) PBX (casual calling)
V = 1-, 10XXX1-, 976, 900 (SENDS ANI7) OCP (NC ONLY) (casual calling)

EXAMPLE:

A								
---	--	--	--	--	--	--	--	--

**** TBE - Toll Billing Exception**

This data field has been deleted in this version.

21. FPI - Freeze PIC Indicator

Identifies the customer's requested freeze option for the LPIC.

USAGE: This field is conditional.

Prohibited when the NPT field is "B" or "D," otherwise optional.

DATA CHARACTERISTICS: 1 alpha character

VALID ENTRIES: A = Freeze Intra
S = Remove Intra Freeze

EXAMPLE:

A

22. LPIC - IntraLATA Presubscription Indicator Code

Identifies the presubscription indicator code (PIC) of the carrier the customer has selected for IntraLATA traffic for the ported telephone number.

USAGE: This field is conditional.

Prohibited when the NPT field is "B" or "D," otherwise optional.

DATA CHARACTERISTICS: 4 alphanumeric characters.

VALID ENTRIES: Valid PIC Code
None = Customer does not want to presubscribe
NA = Not Applicable - Service may not require a PIC or used in a conversion as is scenario.
NC = No Change - Used in a conversion as is activity scenario or change activity when the LPIC is not impacted
UNDC = Undecided (Customer has not decided which presubscribed carrier to select.)

EXAMPLE:

0	4	4	0
---	---	---	---

23. TC OPT - Transfer of Call Options

Identifies the type of transfer of call option requested by the end user for the disconnected telephone number when the standard intercept report is not desirable.

USAGE: This field is conditional.

Prohibited when NPT = D, otherwise optional.

The following standard intercept recordings will automatically apply when this field is not populated.

<u>Order or Line Activity</u>	<u>Standard Intercept Report</u>
"D" - Disconnect	The number you have reached has been disconnected.
"C" or "T" - Number change to a Non-Pub number	The number you have reached XXX-XXXX has been changed to a non-published number.
"C" or "T" - Number change to a listed number	The number you have reached XXX-XXXX has been changed. The new number is XXX-XXXX.
"C" - Seasonal suspension	At the customer's request XXX-XXXX has been temporarily disconnected.
"C" - Disconnect RingMaster number refer calls to Main Number	The number you have reached XXX-XXXX has been changed. The new number is XXX-XXXX.

DATA CHARACTERISTICS: 3 alphanumeric characters.

VALID ENTRIES: Intercept Report

NO = The number you have reached has been disconnected.

TC = The number you have reached XXX-XXXX has been changed. The new number is XXX-XXXX.

CA = The number you have reached has been disconnected. (Used to cancel a transfer of call option when a number is disconnected.)

EXAMPLE:

N	O	
---	---	--

24. TC TO - Transfer of Calls To

Identifies the telephone number to which calls are to be referred.

USAGE: This field is conditional.

Required when the TC OPT field is not TC," otherwise prohibited.

DATA CHARACTERISTICS: 12 numeric characters. (including 2 preprinted hyphens)

EXAMPLE:

2	0	1	-	6	9	9	-	1	2	3	4
---	---	---	---	---	---	---	---	---	---	---	---

25. TC PER - Transfer of Calls Period

Indicates the requested date that the transfer of calls, specified in the TC TO field, is to be removed and the standard recorded announcement is to be provided. When the standard period of transfer (provided by the provider) is acceptable, the field is to be left blank.

VALID ENTRIES: Two Digit Month (01-12)
Two Digit Day (01-31)
Two Digit Century (00-99)
Two Digit Year (00-99)

USAGE: This field is conditional.

Required when the TC TO field is populated, otherwise prohibited.

DATA CHARACTERISTICS: 10 alphanumeric characters. (including 2 hyphens)

EXAMPLES:

0	8	-	1	0	-	1	9	9	6
---	---	---	---	---	---	---	---	---	---

[illegible]

ALPHABETIC/NUMERIC CROSS REFERENCE GLOSSARY NUMBER PORTABILITY FORM

The following table is an alphanumeric cross-reference glossary of the NP Form fields.

	Field Abbreviation	Field #	Field Name
*	AN	3	Account Number
*	ATN	4	Account Telephone Number
*	BA	19	Blocking Activity
*	BLOCK	20	Block
	CFTN	15	Call Forward To Number
	CKR	8	Customer Circuit Reference
	ECCKT	12	Exchange Company Circuit ID
	FPI	21	Freeze PIC Indicator
*	LNA	9	Line Activity
	LPIC	22	IntraLATA Presubscription Indicator
*	LRN	10	Location Routing Number
	NPQTY	5	Number Portability Quantity
	NPT	16	Number Portability Type
	NPTG	18	Number Portability Trunk Group
	PG ___ OF ___	6	Page ___ of ___
	PON	1	Purchase Order Number
	PORTED #	13	Ported Telephone Number
	REF NUM	7	Reference Number
	REMARKS	26	Remarks
	RTI	17	Route Index
**	TBE	**	Toll Billing Exception
	TC OPT	23	Transfer of Call Options
	TC PER	25	Transfer of Calls Period
	TC TO	24	Transfer of Calls To
*	TDT	11	Ten Digit Trigger
	TNP	14	Total Number of Paths
	VER	2	Version Identification

* This field has been added to this form.

** This field has been deleted from this form.

LOOP SERVICE (LS) FORM

Description

This section describes the Loop Service (LS) form entries. Each field on the LS form is identified and defined. The LS form must always be associated with Local Service Request (LSR) and End User (EU) forms.

These request forms were designed with the intent to require a minimum of input information. Remark fields provide space for clarification required for items not specifically covered by the request forms. Attachments may also be used to provide lengthy data requiring further specification (e.g., hunting patterns, restrictions, or other such details not easily described through a standard form entry).

This document incorporates the following BellSouth requirements for the population of form entries:

- Required means the field must be populated.
- Optional means the field may or may not be populated.
- Prohibited means the field must not be populated.
- Conditional means the field is dependent upon the relationship to another entry as specified in the usage statement and is dependent upon the presence, absence or combination of other data entries.

All local service ordering forms utilize the following general instructions for justification:

- Quantity fields are right justified.
- Fields with text are left justified.
- Fields not following these justification rules are so noted within the context of the definition and usage statement.
- If a field is designated as prohibited, it should be left blank.

Administrative Section

1. PON - Purchase Order Number

Identifies the customer's unique purchase order or requisition number that authorizes the issuance of this request or supplement.

USAGE: This field is required.

DATA CHARACTERISTICS: 16 alphanumeric characters.

EXAMPLE:

8	2	4	Z	9											
---	---	---	---	---	--	--	--	--	--	--	--	--	--	--	--

2. VER - Version Identification

Identifies the customer's version number.

USAGE: This field is conditional.

Required when the VER field on the LSR form is populated, otherwise prohibited.

The entry must be identical to the VER field entry on the LSR form.

DATA CHARACTERISTICS: 2 alpha characters.

EXAMPLE:

0	1
---	---

3. AN - Account Number

Identifies the main account number assigned by the NSP. If a number is used, it may or may not be the same as the working telephone number.

USAGE: This field is conditional.

Required when the ATN field is not populated.

Otherwise optional.

DATA CHARACTERISTICS: 20 alphanumeric characters.

EXAMPLE:

N																			
---	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

4. ATN - Account Telephone Number

Identifies the account telephone number assigned by the NSP.

If the number is used, it may or may not be the same as the working telephone number.

The LOCBAN field information used in the previous form version should be used here.

USAGE: This field is conditional.

Required when the AN field is not populated.
Otherwise optional.

DATA CHARACTERISTICS: 12 alphanumeric characters (including 2 preprinted hyphens).

EXAMPLE:

2	0	1	-	5	5	5	-	1	2	1	2
---	---	---	---	---	---	---	---	---	---	---	---

5. LQTY - Loop Quantity

Identifies the quantity of loops involved in this service request.

USAGE: This field is required.

DATA CHARACTERISTICS: 3 numeric characters.

EXAMPLE:

		8
--	--	---

6. PG ____ of ____

Identifies the page number and total number of pages contained in this transaction.

USAGE: This field is required.

DATA CHARACTERISTICS: 4 numeric characters.

EXAMPLE: PG

	1
--	---

 of

	2
--	---

7. **REF NUM - Reference Number**

USAGE: This field is required.

EXAMPLES: | 0 | 0 | 2 | 3

Identifies the circuit number assigned by the customer. It is used by the customer as a cross reference to the provider circuit ID and in many cases to identify the customer's end-to-end service.

DATA CHARACTERISTICS: 36 alphanumeric characters.

[illegible]

9. LNA - Line Activity

Identifies the activity involved at the line level.

USAGE: This field is required.

DATA CHARACTERISTICS: 1 alpha character

VALID ENTRIES: A = New installation and/or account
C = Change an existing account, e.g., rearrangement, partial disconnect or addition
D = Disconnection
M = Inside move of the physical termination within a building
T = Outside move of end user location
R = Record activity is for ordering administrative changes
V = Conversion of service to new LSP

EXAMPLE:

A

10. TSP - Telecommunications Service Priority

Indicates the provisioning and restoration priority as defined under the TSP Service Vendor Handbook. These codes are assigned by the TSP program Office.

USAGE: This field is optional.

A TSP code ending in "00" indicates "revocation," the removal of a previously assigned TSP code.

DATA CHARACTERISTICS: 12 numeric characters (including 1 preprinted hyphen).

VALID ENTRIES

Nine Character TSP Control Identifier
One Character Provisioning Priority Level (E, 0-5)
One Digit Restoration Priority Level (0-5)

EXAMPLE:

T	S	P	1	2	3	4	5	C	-	E	1
---	---	---	---	---	---	---	---	---	---	---	---

EXAMPLE:

A	B	1	2	3	4	5	6	7	8				
							.						

12. ECCKT - Exchange Company Circuit ID

Identifies a provider's circuit identification. The format of the field is defined by the provider. All components within the ID should be delimited by either virgules or periods. The layout of the field may be defined by the COMMON LANGUAGE standards. When a component of CLT, CLS and CLF is purposely omitted, the component should still be delimited and compressed to eliminate any spaces. If all positions in a component of CLT, CLS and CLF are not populated, the component should be compressed to eliminate any spaces.

USAGE: This field is conditional

Required when the first position of the ACT field on the LSR Form is "C", "D", "M", "T" or "R", otherwise optional.

DATA CHARACTERISTICS: 36 alphanumeric characters.

EXAMPLES: Telephone Number Format:

Prefix/Service Code and modifier/NPA/NXX/XXXX/ Terminal Number (if applicable). This format may be up to 30 characters in length.

[illegible]

Serial Number Format:

Prefix/Service Code and modifier/Serial Number/ Suffix Code/AP Code/Segment Name (if applicable). This format may be up to 27 characters in length.

[illegible]

Facility ID Format:

Facility Designation/Facility Type/Office A Location/Office Z Location.
This format may be up to 36 characters in length.

[illegible]

13. CFA - Connecting Facility Assignment

Identifies the provider carrier system and channel to be used. The Facility Identification consists of the following elements:

- The Facility Designation which uniquely identifies a particular facility type between two terminal locations (variable length, 1-5 characters).
- The Facility Type which is usually identified through the use of a code set found in the Bellcore Practice BR-795-450-100 (variable length, 1-6 characters).
- The Channel/Pair number of the facility that is being used to provide the service (variable length, 1-5 characters).
- The "A" Location, which is the location of the facility termination that has the lower alphanumeric CLLI code.
- The "Z" Location, which is the location of the facility termination that has the higher alphanumeric CLLI code.
- Virgules (/) are used as delimiters to separate the different elements of the CFA. All element entries of the Connecting Facility Assignment are left justified with no trailing spaces.

USAGE: This field is conditional

Required when utilizing Hi-Cap facilities and the customer has assignment control, otherwise optional.

DATA CHARACTERISTICS: 42 alphanumeric characters.

EXAMPLE:

1	0	1	/	T	1	/	3	/	B	S	T	N	M	A	G	T	O	G	O	/
B	S	T	N	M	A	M	T	C	G	O										

14. System ID - System Identification

Identifies the customer's system to be used in a collocation arrangement.

USAGE: This field is conditional.

Required when the customer has assignment control in a collocation arrangement, otherwise optional.

DATA CHARACTERISTICS: 5 alphanumeric characters.

EXAMPLE:

A	A			
---	---	--	--	--

15. CABLE ID - Cable Identification

Identifies the provider's central office cable to be connected to the customer's collocated equipment.

USAGE: This field is conditional.

Required when the customer has assignment control in a collocation arrangement,
otherwise optional.

DATA CHARACTERISTICS: 5 alphanumeric characters.

EXAMPLE:

X	X	X	0	1
---	---	---	---	---

16. SHELF

Identifies the number assigned to the customer's shelf to be used in a collocation arrangement..

USAGE: This field is conditional.

Required when the customer has assignment control in a collocation arrangement,
otherwise optional.

DATA CHARACTERISTICS: 6 alphanumeric characters.

EXAMPLE:

2	0				
---	---	--	--	--	--

17. SLOT

Identifies the customer's specific connection slot to be used in a collocation arrangement.

USAGE: This field is optional.

Required when the customer has assignment control in a collocation arrangement,
otherwise optional.

DATA CHARACTERISTICS: 6 alphanumeric characters.

EXAMPLE:

0	7				
---	---	--	--	--	--

18. RELAY RACK

A code that identifies the customer's bay/cabinet in a collocation arrangement and may also include the floor and aisle where the specific piece of equipment is located.

USAGE: This field is conditional.

Required when the customer has assignment control in a collocation arrangement, otherwise optional.

DATA CHARACTERISTICS: 10 alphanumeric characters.

EXAMPLE:

1	0	0	0	5	2	-	0	3	
---	---	---	---	---	---	---	---	---	--

19. CHAN/PAIR - Channel/Pair

Identifies the specific channel or pair within the provider's cable to be used for connection.

USAGE: This field is optional.

Required when the provider has assignment control in a collocation arrangement, otherwise optional.

DATA CHARACTERISTICS: 5 alphanumeric characters.

EXAMPLE:

2	4			
---	---	--	--	--

20. JK CODE - Jack Code

Indicates the standard code for the particular registered or non-registered jack used to terminate the service. Familiarization with the FCC's registration rules is requisite for all parties involved for the determination of the proper jack code for a given registered service. Registered jacks used to terminate category 1 and 3 services begin with the designation "RJ".

USAGE: This field is conditional.

Required when the JR field is populated, otherwise prohibited.

DATA CHARACTERISTICS: 5 alphanumeric characters.

EXAMPLE:

R	J	2	1	X
---	---	---	---	---

21. JK NUM - Jack number

Identifies the number of the jack used on end user connections.

When the jack identification is unknown, enter 99 in this field.

USAGE: This field is conditional.

Required when the JK CODE field is populated, otherwise prohibited.

DATA CHARACTERISTICS: 2 alphanumeric characters.

EXAMPLE:

B	2
---	---

22. JK POS - Jack Position

Identifies the position in the jack that a particular service will occupy.

When jack position is unknown, enter 99 in this field to specify next available position.

USAGE: This field is conditional.

Required when the JK CODE field is populated, otherwise prohibited.

DATA CHARACTERISTICS: 2 numeric characters.

EXAMPLE:

9	9
---	---

23. JR - Jack Request

Indicates a request for a new jack.

USAGE: This field is optional.

DATA CHARACTERISTICS: 1 alpha character.

VALID ENTRIES: Y = Yes

EXAMPLE:

Y

7. REF NUM - Reference Number

EXAMPLE: | 0 | 0 | 2 | 3 |

8. **CKR - Customer Circuit Reference**

[illegible]

9. LNA - Line Activity

Identifies the activity involved at the line level.

USAGE: This field is required.

DATA CHARACTERISTICS: 1 alpha character

VALID ENTRIES: C = Change an existing account (e.g., rearrangement, partial disconnect, addition, or transition from INP to LNP).

D = Disconnection

R = Record activity is for ordering administrative changes

V = Conversion of service to new LSP

EXAMPLE:

10. LRN - Location Routing Number

Identifies a number used to uniquely identify a switch that has ported numbers and is used to route a call to the switch that owns the NPA-NXX portion of the LRN.

LRN is a 10-digit number in the form of NPA-NXX-XXXX.

The LRN provided by the NPAC will be used.

This field is **NOT APPLICABLE** for Bell South.

11. TDT - Ten Digit Trigger

Indicates the request for the activation of a ten digit trigger for local routing number portability.

USAGE: This field is optional.

DATA CHARACTERISTICS: 1 alpha character

VALID ENTRIES: Y = Yes

N = No

EXAMPLE:

12. ECCKT - Exchange Company Circuit ID

This field is NOT APPLICABLE for BellSouth.

13. PORTED # - Ported Telephone Number

Identifies the telephone number to be retained.

USAGE: This field is required.

DATA CHARACTERISTICS: 12 numeric characters. (including 2 preprinted hyphens)

EXAMPLE:

9	0	8	-	6	9	9	-	7	0	0	0
---	---	---	---	---	---	---	---	---	---	---	---

14. TNP - Total Number of Paths

Identifies the total number of talk paths, including the initial path, associated with the ported number.

USAGE: This field is conditional.

Required when the ACT field on the LSR Form is "C" or "V" and the NPT field is "B," otherwise prohibited.

DATA CHARACTERISTICS: 3 numeric characters.

VALID ENTRIES: 001 - 999

EXAMPLE:

0	0	1
---	---	---

15. CFTN - Call Forward To Number

Identifies the telephone number to which calls will be directed.

USAGE: This field is conditional.

Required when the ACT field on the LSR Form is "C" or "V" and the NPT field is "B," otherwise prohibited.

DATA CHARACTERISTICS: 12 numeric characters. (including 2 preprinted hyphens)

EXAMPLE:

6	0	9	-	5	5	5	-	1	5	5	5
---	---	---	---	---	---	---	---	---	---	---	---

Before the
FEDERAL COMMUNICATIONS COMMISSION
Washington, D.C. 20554

In the Matter of)	
)	
Application by BellSouth Corporation,)	CC Docket No. 97-231
BellSouth Telecommunications, Inc.,)	
and BellSouth Long Distance, Inc., for)	
Provision of In-Region, InterLATA)	
Services in Louisiana)	

REPLY AFFIDAVIT OF WILLIAM N. STACY